Writing a CD

Kit Tyabandha, PhD

The following procedure is used for writing to a CD.

1. Create the file system by

   `mkisofs -r -o` **cd–image folder/**

2. Test the CD-image by

   `mount -t iso9660 -o ro,loop=/dev/loop0` **cd–image** `/cdrom`

   Examine the files, then

   `umount /cdrom`

3. Find SCSI informations using

   `cdrecord -scanbus`

4. Write the CD with

   `cdrecord -v speed=2 dev=`**scsi–bus, scsi–id, scsi–lun** `-data` **cd–image**